

Valve/Actuator/DIL-Switch Characteristic Overview

Title

Subject

Project

Abstract

This documents describes the characteristics of valve and actuator combinations. Also it describes the DIL Switch function.

Keywords

C_Unrestricted

Related Product(s)

SAX61..., SAV61..., SAY61..., SAL61..., SAT61..., SAS61..., SKB62, SKC62, SKD62

Document Storage

ProjectShare

Document Category

ProjectRecord

Document Number

A6V12050595 / A5W00237508A

Revision

AF

Revision Date

02-Jul-2026

Document Status

Approved

Author

R&D FID DE Zug

Department

DE

Classification

Unrestricted

Responsible

Luca Baroli

Head Product Management V&A

Beat Bühler

Produktmanager V&A

OrgUnit

SI BP CD VAC

SI BP CD VAC

@

luca.baroli@siemens.com

buehler.beat@siemens.com

☎

+41 (79) 416-7154

+41 (79) 215-6104

Company

Siemens Switzerland Ltd

Smart Infrastructure, Global Headquarters

Theilerstrasse 1a, CH-6300 Zug

Classification

Restricted

Technical specifications and availability subject to change without notice.

© Siemens Switzerland Ltd, 2015

Based on Template












Standard;16;2011-09-30;dh3531




Note:






h = 100% means that the actuator plunger is fully extended






Revision History




h = 0% means that the actuator plunger is fully retracted

Actuator acting direction		 Direct acting  Reverse acting  Positioning signal Y: DC 0...10 V 4...20 mA Positioning signal Z: 0...1000 □ — — — — — Acting direction: Direct - - - - - Acting direction: Reverse					
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
	OFF 1 ON 2 DC 0...10 V log = gleichprozentig ON 1 ON 2 DC 4...20 mA lin = linear						
SAX61.03		Yes			VVG41.11 VVG41.12 VVG41.13 VVG41.14 VVG41.15 VVG41.20 VVG41.25 VVG41.32 VVG41.40 VVG41.50 VVG41.15 VVG41.20 VVG41.25 VVG41.32 VVG41.40 VVG41.50 VVG41.1301 VVG41.1401 VVG41.1501 VVG41.2001 VVG41.2501 VVG41.3201 VVG41.4001 VVG41.5001		
SAX61.03		Yes			VVF22.25-.. VVF22.40-.. VVF22.50-40 VVF22.65-63 VVF22.80-100 VXF22.25-.. VXF22.40-.. VXF22.50-40 VXF22.65-63 VXF22.80-100		
SAX61.03		Yes			VVF32.15-.. VVF32.25-.. VVF32.40-.. VVF32.50-40 VVF32.65-63 VVF32.80-100 VXF32.15-.. VXF32.25-.. VXF32.40-.. VXF32.50-40 VXF32.65-63 VXF32.80-100		

SAX61.03		Yes			VVF42.15-..		
					VVF42.20-6.3		
					VVF42.25-..		
					VVF42.32-16		
					VVF42.40-..		
					VVF42.50-..		
					VVF42.65-..		
					VVF42.80-..		
					VVF42.50-40K		
					VVF42.65-63K		
					VVF42.80-100K		
					VVF42.25-..C		
					VVF42.32-16C		
					VVF42.40-..C		
					VVF42.50-..C		
					VVF42.65-..C		
					VVF42.80-..C		
					VVF42.65KC		
					VVF42.80KC		
					VXF42.15-..		
					VXF42.20-6.3		
					VXF42.25-..		
					VXF42.32-16		
					VXF42.40-..		
					VXF42.50-..		
					VXF42.65-..		
					VXF42.80-..		
					VXF42.25-..C		
					VXF42.32-16C		
					VXF42.40-..C		
					VXF42.50-..C		
					VXF42.65-..C		
					VXF42.80-..C		
SAX61.03		Yes			VVF53.15-..		
					VVF53.20-6.3		
					VVF53.25-..		
					VVF53.32-16		
					VVF53.40-..		
					VVF53.50-31.5		
					VVF53.50-40		
					VXF53.15-..		
					VXF53.20-6.3		
					VXF53.25-..		
					VXF53.32-16		
					VXF53.40-..		
					VXF53.50-40		
SAX61.03		No			VVG41.11		
					VVG41.12		
					VVG41.13		
					VVG41.14		
					VVG41.15		
					VVG41.20		
					VVG41.25		
					VVG41.32		
					VVG41.40		
					VVG41.50		
					VXG41.15		
					VXG41.20		
					VXG41.25		
					VXG41.32		
					VXG41.40		
					VXG41.50		
					VXG41.1301		
					VXG41.1401		
					VXG41.1501		
					VXG41.2001		
					VXG41.2501		
					VXG41.3201		
					VXG41.4001		
					VXG41.5001		

SAX61.03		No			VVF22.25-..		
					VVF22.40-..		
					VVF22.50-40		
					VVF22.65-63		
					VVF22.80-100		
					VXF22.25-..		
					VXF22.40-..		
					VXF22.50-40		
					VXF22.65-63		
					VXF22.80-100		
SAX61.03		No			VVF32.15-..		
					VVF32.25-..		
					VVF32.40-..		
					VVF32.50-40		
					VVF32.65-63		
					VVF32.80-100		
					VXF32.15-..		
					VXF32.25-..		
					VXF32.40-..		
					VXF32.50-40		
SAX61.03		No			VVF42.15-..		
					VVF42.20-6.3		
					VVF42.25-..		
					VVF42.32-16		
					VVF42.40-..		
					VVF42.50-..		
					VVF42.65-..		
					VVF42.80-..		
					VVF42.50-40K		
					VVF42.65-63K		
					VVF42.80-100K		
					VVF42.25-..C		
					VVF42.32-16C		
					VVF42.40-..C		
					VVF42.50-..C		
					VVF42.65-..C		
					VVF42.80-..C		
					VVF42.65KC		
					VVF42.80KC		
					VXF42.15-..		
					VXF42.20-6.3		
					VXF42.25-..		
					VXF42.32-16		
					VXF42.40-..		
					VXF42.50-..		
					VXF42.65-..		
					VXF42.80-..		
					VXF42.25..C		
					VXF42.32-16C		
					VXF42.40..C		
VXF42.50..C							
VXF42.65..C							
VXF42.80..C							
SAX61.03		No			VVF53.15-..		
					VVF53.20-6.3		
					VVF53.25-..		
					VVF53.32-16		
					VVF53.40-..		
					VVF53.50-31.5		
					VVF53.50-40		
					VXF53.15-..		
					VXF53.20-6.3		
					VXF53.25-..		
SAX61.03		No			VXF53.32-16		
					VXF53.40-..		
					VXF53.50-40		

SAX61.03/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VVF53.15-...		
							VVF53.20-6.3		
							VVF53.25-...		
							VVF53.32-16		
							VVF53.40-...		
							VVF53.50-31.5		
							VVF53.50-40		
							VVF53.65-63		
							VXF53.15-...		
							VXF53.20-6.3		
SAX61.03/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVG41.11		
							VVG41.12		
							VVG41.13		
							VVG41.14		
							VVG41.15		
							VVG41.20		
							VVG41.25		
							VVG41.32		
							VVG41.40		
							VVG41.50		
							VXG41.15		
							VXG41.20		
							VXG41.25		
							VXG41.32		
							VXG41.40		
							VXG41.50		
							VXG41.1301		
							VXG41.1401		
							VXG41.1501		
SAX61.03/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF22.25-...		
							VVF22.40-...		
							VVF22.50-40		
							VVF22.65-63		
							VVF22.80-100		
							VXF22.25-...		
							VXF22.40-...		
							VXF22.50-40		
							VXF22.65-63		
							VXF22.80-100		
SAX61.03/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF32.15-...		
							VVF32.25-...		
							VVF32.40-...		
							VVF32.50-40		
							VVF32.65-63		
							VVF32.80-100		
							VXF32.15-...		
							VXF32.25-...		
							VXF32.40-...		
							VXF32.50-40		
							VXF32.65-63		
							VXF32.80-100		

SAX61.03/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF42.15-...		
							VVF42.20-6.3		
							VVF42.25-...		
							VVF42.32-16		
							VVF42.40-...		
							VVF42.50-...		
							VVF42.65-...		
							VVF42.80-...		
							VVF42.50-40K		
							VVF42.65-63K		
							VVF42.80-100K		
							VVF42.25-...C		
							VVF42.32-16C		
							VVF42.40-...C		
							VVF42.50-...C		
							VVF42.65-...C		
							VVF42.80-...C		
SAX61.03/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF42.65KC		
							VVF42.80KC		
							VXF42.15-...		
							VXF42.20-6.3		
							VXF42.25-...		
							VXF42.32-16		
							VXF42.40-...		
							VXF42.50-...		
							VXF42.65-...		
							VXF42.80-...		
							VXF42.25-...C		
							VXF42.32-16C		
							VXF42.40-...C		
							VXF42.50-...C		
							VXF42.65-...C		
							VXF42.80-...C		
SAX61.03/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF53.15-...		
							VVF53.20-6.3		
							VVF53.25-...		
							VVF53.32-16		
							VVF53.40-...		
							VVF53.50-31.5		
							VVF53.50-40		
							VVF53.65-63		
							VVF53.15-...		
							VVF53.20-6.3		
							VVF53.25-...		
							VVF53.32-16		
							VVF53.40-...		
							VVF53.50-40		
							VVF53.65-63		
							VVF53.15-...		
							VVF53.20-6.3		
							VVF53.25-...		
							VVF53.32-16		
							VVF53.40-...		
							VVF53.50-40		
							VVF53.65-63		
							VVF53.15-...		
							VVF53.20-6.3		
							VVF53.25-...		
							VVF53.32-16		
							VVF53.40-...		
							VVF53.50-40		

Actuator acting direction		Acting direction: Direct Acting direction: Reverse V 100 % 0 % 0 V 4 mA 0 Ω 10 V 20 mA 1000 Ω Y 4040Z13 Direct acting 100 % 0 % Y 4040Z15 Positioning signal Y: DC 0...10 V 4...20 mA 0...1000 □ Reverse acting 0 % 100 % Y 4040Z14 Positioning signal Z: DC 0...10 V 4...20 mA 0...1000 □							
		Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
			OFF 1 ON 2 DC 0...10 V log = gleichprozentig ON 1 ON 2 DC 4...20 mA lin = linear		h [%] 100 0 Y [%]	h [%] 100 0 U [%]		V [%] 100 0 h [%]	V [%] 100 0 Y [%]
SAX61P03	ON 1 2	Yes			VPF43.50F15 VPF43.50F25 VPF43.65F25 VPF43.65F35 VPF43.80F35 VPF43.80F45 VPF44.50F15 VPF44.50F25 VPF44.65F25 VPF44.65F35 VPF44.80F35 VPF44.80F45 VPF53.50F15 VPF53.50F25 VPF53.65F25 VPF53.65F35 VPF53.80F35 VPF53.80F45 VPF54.50F15 VPF54.50F25 VPF54.65F25 VPF54.65F35 VPF54.80F35 VPF54.80F45				
SAX61P03	ON 1 2	No			VPF43.50F15 VPF43.50F25 VPF43.65F25 VPF43.65F35 VPF43.80F35 VPF43.80F45 VPF44.50F15 VPF44.50F25 VPF44.65F25 VPF44.65F35 VPF44.80F35 VPF44.80F45 VPF53.50F15 VPF53.50F25 VPF53.65F25 VPF53.65F35 VPF53.80F35 VPF53.80F45 VPF54.50F15 VPF54.50F25 VPF54.65F25 VPF54.65F35 VPF54.80F35 VPF54.80F45				


Actuator acting direction		Acting direction: Direct Acting direction: Reverse							
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
SAX61P03/MO		Yes			LOG (Reg 263 = 1) (Reg 264 = 1400)	Yes	VPF43.50F15 VPF43.50F25 VPF43.65F25 VPF43.65F35 VPF43.80F35 VPF43.80F45 VPF44.50F15 VPF44.50F25 VPF44.65F25 VPF44.65F35 VPF44.80F35 VPF44.80F45 VPF53.50F15 VPF53.50F25 VPF53.65F25 VPF53.65F35 VPF53.80F35 VPF53.80F45 VPF54.50F15 VPF54.50F25 VPF54.65F25 VPF54.65F35 VPF54.80F35 VPF54.80F45		
SAX61P03/MO		No			LIN (Reg 263 = 0) (Reg 264 = 400)	No	VPF43.50F15 VPF43.50F25 VPF43.65F25 VPF43.65F35 VPF43.80F35 VPF43.80F45 VPF44.50F15 VPF44.50F25 VPF44.65F25 VPF44.65F35 VPF44.80F35 VPF44.80F45 VPF53.50F15 VPF53.50F25 VPF53.65F25 VPF53.65F35 VPF53.80F35 VPF53.80F45 VPF54.50F15 VPF54.50F25 VPF54.65F25 VPF54.65F35 VPF54.80F35 VPF54.80F45		



Actuator acting direction			Direct acting	Reverse acting
	Positioning signal Y: DC 0...10 V 4...20 mA Positioning signal Z: 0...1000 ☐		4040Z14 4040Z15	
	———— Acting direction: Direct - - - - Acting direction: Reverse			







Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
	OFF ¹⁾ ON DC 0...10 V DC 4...20 mA log = gleichprozentig lin = linear						




*This setting can lead to strong oscillation behavior. This setting should be avoided if possible.











SAV61.00		Yes			VVF22.40-..		
					VVF22.50-40		
					VVF22.65-63		
					VVF22.80-100		
					VVF22.100-160		
					VXF22.40-..		
SAV61.00		Yes			VVF22.50-40		
					VVF22.65-63		
					VVF22.80-100		
					VVF22.100-160		
					VVF32.100-160		
					VVF32.125-250		
					VVF32.150-400		
					VXF32.100-160		
					VXF32.125-250		
					VXF32.150-400		

SAV61.00		Yes			VVF42.40-16		
					VVF42.40-25		
					VVF42.50-31.5		
					VVF42.50-40		
					VVF42.65-50		
					VVF42.65-63		
					VVF42.80-80		
					VVF42.80-100		
					VVF42.100-125		
					VVF42.100-160		
					VVF42.100-160K		
					VVF42.40-..C		
					VVF42.50-..C		
					VVF42.65-..C		
					VVF42.80-..C		
					VVF42.100-..C		
					VVF42.125-..C		
					VVF42.150-..C		
					VVF42.100KC		
					VVF42.125KC		
					VVF42.150KC		
					VVF42.125-200		
					VVF42.125-250		
					VVF42.125-250K		
					VVF42.150-315		
					VVF42.150-360K		
					VVF42.150-400		
					VXF42.40-16		
					VXF42.40-25		
					VXF42.50-31.5		
					VXF42.50-40		
					VXF42.65-50		
					VXF42.65-63		
					VXF42.80-80		
					VXF42.80-100		
					VXF42.100-125		
					VXF42.100-160		
					VXF42.40-..C		
					VXF42.50-..C		
					VXF42.65-..C		
					VXF42.80-..C		
					VXF42.100-..C		
					VXF42.125-200		
					VXF42.125-250		
					VXF42.150-315		
					VXF42.150-400		
					VXF42.125-..C		
					VXF42.150-..C		






SAV61.00		Yes			VVF43.65-50		
					VVF43.65-63		
					VVF43.80-80		
					VVF43.80-100		
					VVF43.100-125		
					VVF43.100-160		
					VVF43.125-200		
					VVF43.125-250		
					VVF43.150-315		
					VVF43.150-400		
					VXF43.65-50		
					VXF43.65-63		
					VXF43.80-80		
					VXF43.80-100		
					VXF43.100-125		
					VXF43.100-160		
					VXF43.125-200		
					VXF43.125-250		
					VXF43.150-315		
					VXF43.150-400		
SAV61.00		Yes			VVF53.40-12.5		
					VVF53.40-16		
					VVF53.40-20		
					VVF53.40-25		
					VVF53.50-31.5		
					VVF53.50-40		
					VVF53.65-63		
					VVF53.80-100		
					VVF53.100-160		
					VVF53.125-250		
					VVF53.150-400		
					VXF53.40-16		
					VXF53.40-25		
					VXF53.50-40		
					VXF53.65-63		
					VXF53.80-100		
					VXF53.100-160		
					VXF53.125-250		
					VXF53.150-400		


SAV61.00		No			VVF22.40-..		
					VVF22.50-40		
					VVF22.65-63		
					VVF22.80-100		
					VVF22.100-160		
					VXF22.40-..		
					VXF22.50-40		
					VXF22.65-63		
SAV61.00		Yes			VXF22.80-100		
					VXF22.100-160		
					VVF32.100-160		
					VVF32.125-250 *		
					VVF32.150-400 *		
					VXF32.100-160		
					VXF32.125-250 *		
					VXF32.150-400 *		
SAV61.00		No			VVF42.40-16		
					VVF42.40-25		
					VVF42.50-31.5		
					VVF42.50-40		
					VVF42.65-50		
					VVF42.65-63		
					VVF42.80-80		
					VVF42.80-100		
					VVF42.100-125		
					VVF42.100-160		
					VVF42.100-160K		
					VVF42.40-..C		
					VVF42.50-..C		
					VVF42.65-..C		
					VVF42.80-..C		
					VVF42.100-..C		
					VVF42.100KC		
					VVF42.125-200 *		
					VVF42.125-250 *		
					VVF42.125-250K *		
					VVF42.150-315 *		
					VVF42.150-360K *		
					VVF42.150-400 *		
					VVF42.125-..C		
					VVF42.150-..C		
					VVF42.125KC		
					VVF42.150KC		
					VXF42.40-16		
					VXF42.40-25		
					VXF42.50-31.5		
					VXF42.50-40		
					VXF42.65-50		
					VXF42.65-63		
					VXF42.80-80		
					VXF42.80-100		
					VXF42.100-125		
					VXF42.100-160		
					VXF42.40-..C		
					VXF42.50-..C		
					VXF42.65-..C		
					VXF42.80-..C		
					VXF42.100-..C		
					VXF42.125-200 *		
					VXF42.125-250 *		
					VXF42.150-315 *		
					VXF42.150-400 *		
					VXF42.125-..C		
					VXF42.150-..C		
					VXF42.150-..C		

SAV61.00		No			VVF43.65-50		
					VVF43.65-63		
					VVF43.80-80		
					VVF43.80-100		
					VVF43.100-125		
					VVF43.100-160		
					VVF43.125-200 *		
					VVF43.125-250 *		
					VVF43.150-315 *		
					VVF43.150-400 *		
					VXF43.65-50		
					VXF43.65-63		
					VXF43.80-80		
					VXF43.80-100		
					VXF43.100-125		
					VXF43.100-160		
					VXF43.125-200 *		
					VXF43.125-250 *		
					VXF43.150-315 *		
					VXF43.150-400 *		
SAV61.00		No			VVF53.40-12.5		
					VVF53.40-16		
					VVF53.40-20		
					VVF53.40-25		
					VVF53.50-31.5		
					VVF53.50-40		
					VVF53.65-63		
					VVF53.80-100		
					VVF53.100-160		
					VVF53.125-250 *		
					VVF53.150-400 *		
					VXF53.40-16		
					VXF53.40-25		
					VXF53.50-40		
					VXF53.65-63		
					VXF53.80-100		
					VXF53.100-160		
					VXF53.125-250 *		
					VXF53.150-400 *		

Actuator acting direction		 Direct acting  Reverse acting  — Acting direction: Direct — Acting direction: Reverse							
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
	OFF 1 ON 2 DC 0...10 V DC 4...20 mA log = gleichprozentig lin = linear								
*This setting can lead to strong oscillation behavior. This setting should be avoided if possible.									
SAV61.00/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VVF22.40-... VVF22.50-40 VVF22.65-63 VVF22.80-100 VVF22.100-160 VXF22.40-... VXF22.50-40 VXF22.65-63 VXF22.80-100 VXF22.100-160		
SAV61.00/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VVF32.100-160 VVF32.125-250 VVF32.150-400 VXF32.100-160 VXF32.125-250 VXF32.150-400		
SAV61.00/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VVF42.40-16 VVF42.40-25 VVF42.50-31.5 VVF42.50-40 VVF42.65-50 VVF42.65-63 VVF42.80-80 VVF42.80-100 VVF42.100-125 VVF42.100-160 VVF42.100-160K VVF42.40-...C VVF42.50-...C VVF42.65-...C VVF42.80-...C VVF42.100-...C VVF42.100KC VVF42.125-200 VVF42.125-250 VVF42.125-250K VVF42.150-315 VVF42.150-360K VVF42.150-400 VVF42.125-...C VVF42.150-...C VVF42.125KC VVF42.150KC VXF42.40-16 VXF42.40-25 VXF42.50-31.5 VXF42.50-40 VXF42.65-50 VXF42.65-63 VXF42.80-80 VXF42.80-100 VXF42.100-125 VXF42.100-160 VXF42.40-...C VXF42.50-...C VXF42.65-...C VXF42.80-...C VXF42.100-...C VXF42.125-200 VXF42.125-250 VXF42.150-315 VXF42.150-400 VXF42.125-...C VXF42.150-...C		

SAV61.00/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VVF43.65-50		
							VVF43.65-63		
							VVF43.80-80		
							VVF43.80-100		
							VVF43.100-125		
							VVF43.100-160		
							VVF43.125-200		
							VVF43.125-250		
							VVF43.150-315		
							VVF43.150-400		
SAV61.00/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VXF43.65-50		
							VXF43.65-63		
							VXF43.80-80		
							VXF43.80-100		
							VXF43.100-125		
							VXF43.100-160		
							VXF43.125-200		
							VXF43.125-250		
							VXF43.150-315		
							VXF43.150-400		
SAV61.00/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VVF53.40-12.5		
							VVF53.40-16		
							VVF53.40-20		
							VVF53.40-25		
							VVF53.50-31.5		
							VVF53.50-40		
							VVF53.65-63		
							VVF53.80-100		
							VVF53.100-160		
							VVF53.125-250		
SAV61.00/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF22.40-...		
							VVF22.50-40		
							VVF22.65-63		
							VVF22.80-100		
							VVF22.100-160		
							VXF22.40-...		
							VXF22.50-40		
							VXF22.65-63		
							VXF22.80-100		
							VXF22.100-160		
SAV61.00/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF32.100-160		
							VVF32.125-250 *		
							VVF32.150-400 *		
							VXF32.100-160		
							VXF32.125-250 *		
							VXF32.150-400 *		

















SAV61.00/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF42.40-16		
							VVF42.40-25		
							VVF42.50-31.5		
							VVF42.50-40		
							VVF42.65-50		
							VVF42.65-63		
							VVF42.80-80		
							VVF42.80-100		
							VVF42.100-125		
							VVF42.100-160		
							VVF42.100-160K		
							VVF42.40-...C		
							VVF42.50-...C		
							VVF42.65-...C		
							VVF42.80-...C		
							VVF42.100-...C		
							VVF42.100KC		
							VVF42.125KC		
							VVF42.150KC		
							VVF42.125-200 *		
							VVF42.125-250 *		
							VVF42.125-250K *		
							VVF42.125-...C		
							VVF42.150-...C		
							VVF42.150-315 *		
							VVF42.150-360K *		
							VVF42.150-400 *		
							VXF42.40-16		
							VXF42.40-25		
							VXF42.50-31.5		
							VXF42.50-40		
							VXF42.65-50		
							VXF42.65-63		
							VXF42.80-80		
							VXF42.80-100		
							VXF42.100-125		
							VXF42.100-160		
							VXF42.40...C		
							VXF42.50...C		
							VXF42.65...C		
							VXF42.80...C		
							VXF42.100...C		
							VXF42.125-200 *		
							VXF42.125-250 *		
							VXF42.150-315 *		
							VXF42.150-400 *		
							VXF42.125...C		
							VXF42.150...C		
SAV61.00/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF43.65-50		
							VVF43.65-63		
							VVF43.80-80		
							VVF43.80-100		
							VVF43.100-125		
							VVF43.100-160		
							VVF43.125-200 *		
							VVF43.125-250 *		
							VVF43.150-315 *		
							VVF43.150-400 *		
							VXF43.65-50		
							VXF43.65-63		
							VXF43.80-80		
							VXF43.80-100		
							VXF43.100-125		
							VXF43.100-160		
							VXF43.125-200 *		
							VXF43.125-250 *		
							VXF43.150-315 *		
							VXF43.150-400 *		

SAV61.00/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF53.40-12.5		
							VVF53.40-16		
							VVF53.40-20		
							VVF53.40-25		
							VVF53.50-31.5		
							VVF53.50-40		
							VVF53.65-63		
							VVF53.80-100		
							VVF53.100-160		
							VVF53.125-250 *		
							VVF53.150-400 *		
							VXF53.40-16		
							VXF53.40-25		
							VXF53.50-40		
							VXF53.65-63		
							VXF53.80-100		
							VXF53.100-160		
							VXF53.125-250 *		
							VXF53.150-400 *		

Actuator acting direction		<table><tr><td></td><td>Acting direction: Direct</td></tr><tr><td></td><td>Acting direction: Reverse</td></tr></table>							Acting direction: Direct		Acting direction: Reverse						
			Acting direction: Direct														
			Acting direction: Reverse														
0 V 10 V 4 mA 20 mA 0 Ω 1000 Ω		<table><tr><th>Direct acting</th><th>Reverse acting</th></tr><tr><td> Positioning signal Y: DC 0...10 V 4...20 mA 0...1000 □ </td><td> Positioning signal Z: DC 0...10 V 4...20 mA 0...1000 □ </td></tr></table>		Direct acting	Reverse acting	Positioning signal Y: DC 0...10 V 4...20 mA 0...1000 □	Positioning signal Z: DC 0...10 V 4...20 mA 0...1000 □										
Direct acting	Reverse acting																
Positioning signal Y: DC 0...10 V 4...20 mA 0...1000 □	Positioning signal Z: DC 0...10 V 4...20 mA 0...1000 □																
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic										
	<table><tr><td>OFF ¹⁾</td><td></td><td>DC 0...10 V</td><td></td><td>log = gleichprozentig</td></tr><tr><td>ON</td><td></td><td>DC 4...20 mA</td><td></td><td>lin = linear</td></tr></table>	OFF ¹⁾		DC 0...10 V		log = gleichprozentig	ON		DC 4...20 mA		lin = linear						
OFF ¹⁾		DC 0...10 V		log = gleichprozentig													
ON		DC 4...20 mA		lin = linear													
SAV61P00		Yes			VPF43.100F70 VPF43.100F90 VPF43.125F110 VPF43.125F135 VPF43.150F160 VPF43.150F200 VPF43.200F210 VPF43.200F280 VPF44.100F70 VPF44.100F90 VPF44.125F110 VPF44.125F135 VPF44.150F150 VPF44.150F200 VPF53.100F70 VPF53.100F90 VPF53.125F110 VPF53.125F135 VPF53.150F160 VPF53.150F200 VPF53.200F210 VPF53.200F280 VPF54.100F70 VPF54.100F90 VPF54.125F110 VPF54.125F135 VPF54.150F150 VPF54.150F200												
SAV61P00		No			VPF43.100F70 VPF43.100F90 VPF43.125F110 VPF43.125F135 VPF43.150F160 VPF43.150F200 VPF43.200F210 VPF43.200F280 VPF44.100F70 VPF44.100F90 VPF44.125F110 VPF44.125F135 VPF44.150F150 VPF44.150F200 VPF53.100F70 VPF53.100F90 VPF53.125F110 VPF53.125F135 VPF53.150F160 VPF53.150F200 VPF53.200F210 VPF53.200F280 VPF54.100F70 VPF54.100F90 VPF54.125F110 VPF54.125F135 VPF54.150F150 VPF54.150F200												

Actuator acting direction		Acting direction: Direct Acting direction: Reverse Direct acting Reverse acting Positioning signal Y: DC 0...10 V 4...20 mA 0...1000 Ω Positioning signal Z: 0...1000 Ω					
		OFF 1 ON 2 DC 0...10 V log = gleichprozentig ON 1 OFF 2 DC 4...20 mA lin = linear Factory Setting Actuator stroke / angle characteristic Actuator U-Signal Valve ASN VPI46.40F9.5Q VPI46.50F12Q Valve stroke / angle characteristic Actuator + valve characteristic					
SAY61P03		Yes			VPI46.40F9.5Q VPI46.50F12Q		
SAY61P03		No			VPI46.40F9.5Q VPI46.50F12Q		

Actuator acting direction	<table><tr><td colspan="2"></td><td colspan="2">Acting direction: Direct</td><td colspan="5"></td></tr><tr><td colspan="2"></td><td colspan="2">Acting direction: Reverse</td><td colspan="5"></td></tr><tr><td colspan="4"></td><td colspan="2"></td><td colspan="3"></td><td colspan="2"></td></tr></table>											Acting direction: Direct									Acting direction: Reverse																	
			Acting direction: Direct																																			
		Acting direction: Reverse																																				
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic																													
SAY61P03/MO		Yes			LOG (Reg 263 = 1) (Reg 264 = 1400)	Yes	VPI46.40F9.5Q																															
							VPI46.50F12Q																															
SAY61P03/MO		No			LIN (Reg 263 = 0) (Reg 264 = 400)	No	VPI46.40F9.5Q																															
							VPI46.50F12Q																															

Actuator ASN	DIL Switch Config *DIL-2 has no function	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
							
SAL61.03T10		Yes			VBF21.40 VBF21.50 VBF21.65 VBF21.80 VBF21.100 VBF21.125 VBF21.150		
SAL61.03T10		Yes			VKF41.40 VKF41.50 VKF41.65 VKF41.80 VKF41.100 VKF41.125 VKF41.150 VKF41.200		
SAL61.03T10		No*			VBF21.40 VBF21.50 VBF21.65 VBF21.80 VBF21.100 VBF21.125 VBF21.150		
SAL61.03T10		No*			VKF41.40 VKF41.50 VKF41.65 VKF41.80 VKF41.100 VKF41.125 VKF41.150 VKF41.200		
SAL61.03T10/F05		Yes			VFW41.40U VFW41.50U VFW41.65U VFW41.80U VFW41.100U VFW41.125U VFW41.150U VFW41.200U		
SAL61.03T10/F05		No*			VFW41.40U VFW41.50U VFW41.65U VFW41.80U VFW41.100U VFW41.125U VFW41.150U VFW41.200U		

Actuator ASN	DIL Switch Config *DIL-2 has no function	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
SAL61.00T20		Yes			VFW41.40 VFW41.50 VFW41.65		
SAL61.00T20		Yes			VFL41.40 VFL41.50 VFL41.65		
SAL61.00T20		No*			VFW41.40 VFW41.50 VFW41.65		
SAL61.00T20		No*			VFL41.40 VFL41.50 VFL41.65		

Actuator ASN	DIL Switch Config *DIL-2 has no function	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
SAL61.00T40		Yes			VKF41.150		
					VKF41.200		
SAL61.00T40		Yes			VKF46.80		
					VKF46.100		
					VKF46.125		
SAL61.00T40		Yes			VFW41.80		
					VFW41.100		
					VFW41.125		
SAL61.00T40		Yes			VFL41.80		
					VFL41.100		
					VFL41.125		
SAL61.00T40		No*			VKF41.150		
					VKF41.200		
SAL61.00T40		No*			VKF46.80		
					VKF46.100		
					VKF46.125		
SAL61.00T40		No*			VFW41.80		
					VFW41.100		
					VFW41.125		
SAL61.00T40		No*			VFL41.80		
					VFL41.100		
					VFL41.125		

Actuator ASN	DIL Switch Config *DIL-2 has no function	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
SAL61.00T40/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VKF41.150 VKF41.200		
SAL61.00T40/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VKF46.80 VKF46.100 VKF46.125		
SAL61.00T40/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VFW41.80 VFW41.100 VFW41.125		
SAL61.00T40/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VFL41.80 VFL41.100 VFL41.125		
SAL61.00T40/MO		No*			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VKF41.150 VKF41.200		
SAL61.00T40/MO		No*			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VKF46.80 VKF46.100 VKF46.125		
SAL61.00T40/MO		No*			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VFW41.80 VFW41.100 VFW41.125		
SAL61.00T40/MO		No*			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VFL41.80 VFL41.100 VFL41.125		

Actuator ASN	DIL Switch Config				Factory Setting	Actuator stroke / angle characteristic		Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic		Actuator + valve characteristic
	ON	OFF	ON	OFF		h [%]	h [%]			V [%]	V [%]	
			DC 4...20 mA	DC 0...10 V								
			DC 0...10 V	DC 0...10 V								
*This setting can lead to strong oscillation behavior. This setting should be avoided if possible.												
SAT61.51					Yes				VVG549.15-.. VVG549.15-.. VVG549.20-4K VVG549.25-6.3K			
SAT61.51					No				VVG549.15-... * VVG549.15-... * VVG549.20-4K * VVG549.25-6.3K *			

Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
	ON OFF ON OFF DC 4...20 mA DC 0...10 V DC 0...10 V DC 0...10 V lin = linear log = (gleichprozentig)								
*This setting can lead to strong oscillation behavior. This setting should be avoided if possible.									
SAT61.51/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VVG549.15-... VVG549.15-... VVG549.20-4K VVG549.25-6.3K		
SAT61.51/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVG549.15-... * VVG549.15-... * VVG549.20-4K * VVG549.25-6.3K *		

Actuator ASN	DIL Switch Config				Factory Setting	Actuator stroke / angle characteristic		Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic		Actuator + valve characteristic
	ON	OFF	ON	OFF		h [%]	h [%]			V [%]	V [%]	
			DC 4...20 mA	DC 0...10 V								
			DC 0...10 V	DC 0...10 V								
*This setting can lead to strong oscillation behavior. This setting should be avoided if possible.												
SAT61.008					Yes				VVG549.15-.. VVG549.15-.. VVG549.20-4K VVG549.25-6.3K			
SAT61.008					No				VVG549.15-... * VVG549.15-... * VVG549.20-4K * VVG549.25-6.3K *			

Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
*This setting can lead to strong oscillation behavior. This setting should be avoided if possible.									
SAT61.008/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 400)	Yes	VVG549.15-.. VVG549.15-.. VVG549.20-4K VVG549.25-6.3K		
SAT61.008/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVG549.15-.. * VVG549.15-.. * VVG549.20-4K * VVG549.25-6.3K *		




Actuator ASN	DIL Switch Config		Factory Setting	Actuator stroke / angle characteristic		Valve ASN	Valve stroke / angle characteristic		Actuator + valve characteristic
	ON OFF DC 4...20 mA DC 0...10 V	ON OFF lin = linear log = gleichprozentig		h [%] 100 0 Y [%]	h [%] 100 0 U [%]		V̇ [%] 100 0 h [%]	V̇ [%] 100 0 Y [%]	
SAS61.03		Yes			VVG44.15-... VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25				
SAS61.03		Yes			VXG44.15-... VXG44.20-6.3 VXG44.25-10 VXG44.32-16 VXG44.40-25				
SAS61.03		No			VVG44.15-... VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25				
SAS61.03		No			VXG44.15-... VXG44.20-6.3 VXG44.25-10 VXG44.32-16 VXG44.40-25				





Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
SAS61.03/MO		Yes			LOG (Reg 263 = 1) (Reg 264 = 700)	Yes	VVG44.15-.. VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25		
SAS61.03/MO		Yes			LOG (Reg 263 = 1) (Reg 264 = 700)	Yes	VVG44.15-.. VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25		
SAS61.03/MO		No			LIN (Reg 263 = 0) (Reg 264 = 400)	No	VVG44.15-.. VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25		
SAS61.03/MO		No			LIN (Reg 263 = 0) (Reg 264 = 400)	No	VVG44.15-.. VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25		







Actuator ASN	DIL Switch Config		Factory Setting	Actuator stroke / angle characteristic		Valve ASN	Valve stroke / angle characteristic		Actuator + valve characteristic
	ON OFF	DC 4...20 mA DC 0...10 V	ON OFF	h [%] 0 100 Y [%]	h [%] 0 100 U [%]		V [%] 0 100 h [%]	V [%] 0 100 Y [%]	
SAS61.53		ON OFF	Yes			VVG44.15-... VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25			
SAS61.53		ON OFF	Yes			VXG44.15-... VXG44.20-6.3 VXG44.25-10 VXG44.32-16 VXG44.40-25			
SAS61.53		ON OFF	No			VVG44.15-... VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25			
SAS61.53		ON OFF	No			VXG44.15-... VXG44.20-6.3 VXG44.25-10 VXG44.32-16 VXG44.40-25			


Actuator ASN	DIL Switch Config		Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cabledapter Setting	Modbus Cabledapter Factory Setting	Valve ASN	Valve stroke / angle caracteristic	Actuator + valve characteristic
	ON	OFF								
SAS61.33/MO	ON:  DC 4...20 mA	OFF:  DC 8...10 V	Yes			LOG (Reg 263 = 1) (Reg 264 = 700)	Yes	VVG44.15-.. VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25		
SAS61.33/MO	ON:  DC 4...20 mA	OFF:  DC 8...10 V	Yes			LOG (Reg 263 = 1) (Reg 264 = 700)	Yes	VVG44.15-.. VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25		
SAS61.33/MO	ON:  DC 4...20 mA	OFF:  DC 8...10 V	No			LIN (Reg 263 = 0) (Reg 264 = 400)	No	VVG44.15-.. VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25		
SAS61.33/MO	ON:  DC 4...20 mA	OFF:  DC 8...10 V	No			LIN (Reg 263 = 0) (Reg 264 = 400)	No	VVG44.15-.. VVG44.20-6.3 VVG44.25-10 VVG44.32-16 VVG44.40-25		

Actuator acting direction		Direct acting Reverse acting Positioning signal Y: DC 0...10 V 4...20 mA Positioning signal Z: 0...1000 □ — — — Acting direction: Direct — — — Acting direction: Reverse					
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
	ON OFF DC 4...20 mA DC 0...10 V lin = linear log = gleichprozentig						
SKD62		Yes			VVG41.11...12 VVG41.13 VVG41.14 VVG41.15 VVG41.20 VVG41.25 VVG41.32 VVG41.40 VVG41.50 VXG41.15 VXG41.20 VXG41.25 VXG41.32 VXG41.40 VXG41.50 VXG41.1301 VXG41.1401 VXG41.1501 VXG41.2001 VXG41.2501 VXG41.3201 VXG41.4001 VXG41.5001		
SKD62		Yes			VVF22.25-.. VVF22.40-.. VVF22.50-40 VVF22.65-63 VVF22.80-100 VXF22.25-.. VXF22.40-.. VXF22.50-40 VXF22.65-63 VXF22.80-100		
SKD62		Yes			VVF32.15-.. VVF32.25-.. VVF32.40-.. VVF32.50-40 VVF32.65-63 VVF32.80-100 VXF32.15-.. VXF32.25-.. VXF32.40-.. VXF32.50-40 VXF32.65-63 VXF32.80-100		





SKD62		Yes			VVF42.15-..		
					VVF42.20-6.3		
					VVF42.25-..		
					VVF42.32-16		
					VVF42.40-..		
					VVF42.50-..		
					VVF42.65-..		
					VVF42.80-..		
					VVF42.50-40K		
					VVF42.65-63K		
					VVF42.80-100K		
					VVF42.25-..C		
					VVF42.32-16C		
					VVF42.40-..C		
					VVF42.50-..C		
					VVF42.65-..C		
					VVF42.80-..C		
					VVF42.65KC		
					VVF42.80KC		
					VXF42.15-..		
					VXF42.20-6.3		
					VXF42.25-..		
					VXF42.32-16		
					VXF42.40-..		
					VXF42.50-..		
					VXF42.65-..		
					VXF42.80-..		
					VXF42.25..C		
					VXF42.32-16C		
					VXF42.40..C		
					VXF42.50..C		
					VXF42.65..C		
					VXF42.80..C		
SKD62		Yes			VVF52.65-63KC		
					VVF52.80-100KC		
SKD62		Yes			VVF53.15-..		
					VVF53.20-6.3		
					VVF53.25-..		
					VVF53.32-16		
					VVF53.40-..		
					VVF53.50-31.5		
					VVF53.50-40		
					VVF53.50-40K		
					VXF53.15-..		
					VXF53.20-6.3		
					VXF53.25-..		
					VXF53.32-16		
SKD62		Yes			VVF61.09..11		
					VVF61.12..13		
					VVF61.14..15		
					VVF61.23..25		
					VXF61.14..15		
					VXF61.24..25		








SKB62		Yes			VVF63.15-0.2		
					VVF63.15-0.32		
					VVF63.15-0.5		
					VVF63.15-0.8		
					VVF63.15-1.25		
					VVF63.15-2		
					VVF63.15-3.2		
					VVF63.20-6.3		
					VVF63.25-5		
					VVF63.25-8		
					VVF63.32-16		
					VVF63.40-12.5		
					VVF63.40-20		
					VVF63.50-31.5		
					VVF63.50-40K		
					VVF63.65-50		
					VXF63.15-1.6		
					VXF63.15-2.5		
					VXF63.15-4		
					VXF63.20-6.3		
					VXF63.25-6.3		
					VXF63.25-10		
					VXF63.32-16		
					VXF63.40-16		
					VXF63.40-25		
					VXF63.50-31.5		
SKD62		No			VVG41.11..12		
					VVG41.13		
					VVG41.14		
					VVG41.15		
					VVG41.20		
					VVG41.25		
					VVG41.32		
					VVG41.40		
					VVG41.50		
					VXG41.15		
					VXG41.20		
					VXG41.25		
					VXG41.32		
					VXG41.40		
					VXG41.50		
					VXG41.1301		
					VXG41.1401		
					VXG41.1501		
					VXG41.2001		
					VXG41.2501		
					VXG41.3201		
					VXG41.4001		
					VXG41.5001		
SKD62		No			VVF22.25-..		
					VVF22.40-..		
					VVF22.50-40		
					VVF22.65-63		
					VVF22.80-100		
					VXF22.25-..		
					VXF22.40-..		
					VXF22.50-40		
SKD62		No			VXF22.65-63		
					VXF22.80-100		
					VVF32.15-..		
					VVF32.25-..		
					VVF32.40-..		
					VVF32.50-40		
					VVF32.65-63		
					VVF32.80-100		
					VXF32.15-..		
					VXF32.25-..		
					VXF32.40-..		
					VXF32.50-40		
					VXF32.65-63		
					VXF32.80-100		


SKD62		No			VVF42.15-..		
					VVF42.20-6.3		
					VVF42.25-..		
					VVF42.32-16		
					VVF42.40-..		
					VVF42.50-..		
					VVF42.65-..		
					VVF42.80-..		
					VVF42.50-40K		
					VVF42.65-63K		
					VVF42.80-100K		
					VVF42.25-..C		
					VVF42.32-16C		
					VVF42.40-..C		
					VVF42.50-..C		
					VVF42.65-..C		
					VVF42.80-..C		
					VVF42.65KC		
					VVF42.80KC		
					VXF42.15-..		
					VXF42.20-6.3		
					VXF42.25-..		
					VXF42.32-16		
					VXF42.40-..		
					VXF42.50-..		
					VXF42.65-..		
					VXF42.80-..		
					VXF42.25..C		
					VXF42.32-16C		
					VXF42.40..C		
					VXF42.50..C		
					VXF42.65..C		
					VXF42.80..C		
SKD62		No			VVF52.65-63KC		
					VVF52.80-100KC		
SKD62		No			VVF53.15-..		
					VVF53.20-6.3		
					VVF53.25-..		
					VVF53.32-16		
					VVF53.40-..		
					VVF53.50-31.5		
					VVF53.50-40		
					VVF53.50-40K		
					VXF53.15-..		
					VXF53.20-6.3		
					VXF53.25-..		
					VXF53.32-16		
					VXF53.40-..		
					VXF53.50-40		
SKD62		No			VVF61.09..11		
					VVF61.12..13		
					VVF61.14..15		
					VVF61.23..25		
					VXF61.14..15		
					VXF61.24..25		

SKD62		No			VVF63.15-0.2		
					VVF63.15-0.32		
					VVF63.15-0.5		
					VVF63.15-0.8		
					VVF63.15-1.25		
					VVF63.15-2		
					VVF63.15-3.2		
					VVF63.20-6.3		
					VVF63.25-5		
					VVF63.25-8		
					VVF63.32-16		
					VVF63.40-12.5		
					VVF63.40-20		
					VVF63.50-31.5		
					VVF63.50-40K		
					VVF63.65-50		
					VXF63.15-1.6		
					VXF63.15-2.5		
					VXF63.15-4		
					VXF63.20-6.3		
					VXF63.25-6.3		
					VXF63.25-10		
					VXF63.32-16		
					VXF63.40-16		
					VXF63.40-25		
					VXF63.50-31.5		







Actuator acting direction		Direct acting Reverse acting Acting direction: Direct Acting direction: Reverse							
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
SKD62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVG41.11..12 VVG41.13 VVG41.14 VVG41.15 VVG41.20 VVG41.25 VVG41.32 VVG41.40 VVG41.50 VVG41.15 VVG41.20 VVG41.25 VVG41.32 VVG41.40 VVG41.50 VVG41.1301 VVG41.1401 VVG41.1501 VVG41.2001 VVG41.2501 VVG41.3201 VVG41.4001 VVG41.5001		
SKD62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF22.25-... VVF22.40-... VVF22.50-40 VVF22.65-63 VVF22.80-100 VVF22.25-... VVF22.40-... VVF22.50-40 VVF22.65-63 VVF22.80-100		
SKD62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF32.15-... VVF32.25-... VVF32.40-... VVF32.50-40 VVF32.65-63 VVF32.80-100 VVF32.15-... VVF32.25-... VVF32.40-... VVF32.50-40 VVF32.65-63 VVF32.80-100		
SKD62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF42.15-... VVF42.20-6.3 VVF42.25-... VVF42.32-16 VVF42.40-... VVF42.50-... VVF42.65-... VVF42.80-... VVF42.50-40K VVF42.65-63K VVF42.80-100K VVF42.25-...C VVF42.32-16C VVF42.40-...C VVF42.50-...C VVF42.65-...C VVF42.80-...C VVF42.65KC VVF42.80KC VVF42.15-... VVF42.20-6.3 VVF42.25-... VVF42.32-16 VVF42.40-... VVF42.50-... VVF42.65-... VVF42.80-... VVF42.25-...C VVF42.32-16C VVF42.40-...C VVF42.50-...C VVF42.65-...C VVF42.80-...C		
SKD62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF52.65-63KC VVF52.80-100KC		




SKD62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF53.15-...		
							VVF53.20-6.3		
							VVF53.25-...		
							VVF53.32-16		
							VVF53.40-...		
							VVF53.50-31.5		
							VVF53.50-40		
							VVF53.50-40K		
							VXF53.15-...		
							VXF53.20-6.3		
							VXF53.25-...		
							VXF53.32-16		
							VXF53.40-...		
SKD62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF61.09..11		
							VVF61.12..13		
							VVF61.14..15		
							VVF61.23..25		
							VXF61.14..15		
SKD62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF63.15-0.2		
							VVF63.15-0.32		
							VVF63.15-0.5		
							VVF63.15-0.8		
							VVF63.15-1.25		
							VVF63.15-2		
							VVF63.15-3.2		
							VVF63.20-6.3		
							VVF63.25-5		
							VVF63.25-8		
							VVF63.32-16		
							VVF63.40-12.5		
							VVF63.40-20		
							VVF63.50-31.5		
							VVF63.50-40K		
							VVF63.65-50		
							VXF63.15-1.6		
							VXF63.15-2.5		
							VXF63.15-4		
							VXF63.20-6.3		
							VXF63.25-6.3		
							VXF63.25-10		
							VXF63.32-16		
							VXF63.40-16		
							VXF63.40-25		
							VXF63.50-31.5		
SKD62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVG41.11..12		
							VVG41.13		
							VVG41.14		
							VVG41.15		
							VVG41.20		
							VVG41.25		
							VVG41.32		
							VVG41.40		
							VVG41.50		
							VXG41.15		
							VXG41.20		
							VXG41.25		
							VXG41.32		
							VXG41.40		
							VXG41.50		
							VXG41.1301		
							VXG41.1401		
							VXG41.1501		
							VXG41.2001		
							VXG41.2501		
							VXG41.3201		
							VXG41.4001		
							VXG41.5001		





SKD62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF22.25-...		
							VVF22.40-...		
							VVF22.50-40		
							VVF22.65-63		
							VVF22.80-100		
							VXF22.25-...		
							VXF22.40-...		
SKD62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF32.15-...		
							VVF32.25-...		
							VVF32.40-...		
							VVF32.50-40		
							VVF32.65-63		
							VVF32.80-100		
							VXF32.15-...		
SKD62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF42.15-...		
							VVF42.20-6.3		
							VVF42.25-...		
							VVF42.32-16		
							VVF42.40-...		
							VVF42.50-...		
							VVF42.65-...		
							VVF42.80-...		
							VVF42.50-40K		
							VVF42.65-63K		
							VVF42.80-100K		
							VVF42.25-...C		
							VVF42.32-16C		
							VVF42.40-...C		
							VVF42.50-...C		
							VVF42.65-...C		
							VVF42.80-...C		
							VVF42.65KC		
							VVF42.80KC		
							VXF42.15-...		
							VXF42.20-6.3		
							VXF42.25-...		
							VXF42.32-16		
							VXF42.40-...		
							VXF42.50-...		
							VXF42.65-...		
							VXF42.80-...		
							VXF42.25...C		
							VXF42.32-16C		
							VXF42.40...C		
							VXF42.50...C		
SKD62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF52.65-63KC		
							VVF52.80-100KC		
SKD62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF53.15-...		
							VVF53.20-6.3		
							VVF53.25-...		
							VVF53.32-16		
							VVF53.40-...		
							VVF53.50-31.5		
							VVF53.50-40		
							VVF53.50-40K		
							VXF53.15-...		
							VXF53.20-6.3		
							VXF53.25-...		
							VXF53.32-16		
SKD62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF53.40-...		
							VXF53.50-40		
							VVF61.09...11		
							VVF61.12...13		
							VVF61.14...15		
							VVF61.23...25		
							VXF61.14...15		
SKD62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF61.24...25		


SKD62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF63.15-0.2		
							VVF63.15-0.32		
							VVF63.15-0.5		
							VVF63.15-0.8		
							VVF63.15-1.25		
							VVF63.15-2		
							VVF63.15-3.2		
							VVF63.20-6.3		
							VVF63.25-5		
							VVF63.25-8		
							VVF63.32-16		
							VVF63.40-12.5		
							VVF63.40-20		
							VVF63.50-31.5		
							VVF63.50-40K		
							VVF63.65-50		
							VXF63.15-1.6		
							VXF63.15-2.5		
							VXF63.15-4		
							VXF63.20-6.3		
							VXF63.25-6.3		
							VXF63.25-10		
							VXF63.32-16		
							VXF63.40-16		
							VXF63.40-25		
							VXF63.50-31.5		










Actuator acting direction		Direct acting Reverse acting Positioning signal Y: DC 0...10 V 4...20 mA Positioning signal Z: 0...1000 □ — Acting direction: Direct — Acting direction: Reverse					
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
	ON DC 4...20 mA OFF DC 0...10 V lin = linear log = gleichprozentig						
SKB62		Yes			VVG41.11...12 VVG41.13 VVG41.14 VVG41.15 VVG41.20 VVG41.25 VVG41.32 VVG41.40 VVG41.50 VVG41.15 VVG41.20 VVG41.25 VVG41.32 VVG41.40 VVG41.50 VVG41.1301 VVG41.1401 VVG41.1501 VVG41.2001 VVG41.2501 VVG41.3201 VVG41.4001 VVG41.5001		
SKB62		Yes			VVF22.25-.. VVF22.40-.. VVF22.50-40 VVF22.65-63 VVF22.80-100 VXF22.25-.. VXF22.40-.. VXF22.50-40 VXF22.65-63 VXF22.80-100		
SKB62		Yes			VVF32.15-.. VVF32.25-.. VVF32.40-.. VVF32.50-40 VVF32.65-63 VVF32.80-100 VXF32.15-.. VXF32.25-.. VXF32.40-.. VXF32.50-40 VXF32.65-63 VXF32.80-100		




SKB62		Yes			VVF42.15-..		
					VVF42.20-6.3		
					VVF42.25-..		
					VVF42.32-16		
					VVF42.40-..		
					VVF42.50-40K		
					VVF42.50-..		
					VVF42.65-..		
					VVF42.65-63K		
					VVF42.80-..		
					VVF42.80-100K		
					VVF42.25-..C		
					VVF42.32-16C		
					VVF42.40-..C		
					VVF42.50-..C		
					VVF42.65-..C		
					VVF42.80-..C		
					VVF42.65KC		
					VVF42.80KC		
					VXF42.15-..		
					VXF42.20-6.3		
					VXF42.25-..		
					VXF42.32-16		
					VXF42.40-..		
					VXF42.50-..		
					VXF42.65-..		
					VXF42.80-..		
					VXF42.25..C		
					VXF42.32-16C		
					VXF42.40..C		
					VXF42.50..C		
SKB62		Yes			VVF52.65-63KC		
					VVF52.80-100KC		
SKB62		Yes			VVF53.15-..		
					VVF53.20-6.3		
					VVF53.25-..		
					VVF53.32-16		
					VVF53.40-..		
					VVF53.50-31.5		
					VVF53.50-40		
					VVF53.50-40K		
					VXF53.15-..		
					VXF53.20-6.3		
					VXF53.25-..		
					VXF53.32-16		
SKB62		Yes			VVF61.09..11		
					VVF61.12..13		
					VVF61.14..15		
					VVF61.23..25		
					VVF61.39..40		
					VVF61.49..50		
					VXF61.14..15		
					VXF61.24..25		
					VXF61.39..40		
					VXF61.49..50		









SKB62		Yes			VVF63.15-0.2		
					VVF63.15-0.32		
					VVF63.15-0.5		
					VVF63.15-0.8		
					VVF63.15-1.25		
					VVF63.15-2		
					VVF63.15-3.2		
					VVF63.20-6.3		
					VVF63.25-5		
					VVF63.25-8		
					VVF63.32-16		
					VVF63.40-12.5		
					VVF63.40-20		
					VVF63.50-31.5		
					VVF63.50-40K		
					VVF63.65-50		
					VXF63.15-1.6		
					VXF63.15-2.5		
					VXF63.15-4		
					VXF63.20-6.3		
					VXF63.25-6.3		
					VXF63.25-10		
					VXF63.32-16		
					VXF63.40-16		
					VXF63.40-25		
					VXF63.50-31.5		
SKB62		No			VVG41.11..12		
					VVG41.13		
					VVG41.14		
					VVG41.15		
					VVG41.20		
					VVG41.25		
					VVG41.32		
					VVG41.40		
					VVG41.50		
					VXG41.15		
					VXG41.20		
					VXG41.25		
					VXG41.32		
					VXG41.40		
					VXG41.50		
					VXG41.1301		
					VXG41.1401		
					VXG41.1501		
					VXG41.2001		
					VXG41.2501		
					VXG41.3201		
					VXG41.4001		
					VXG41.5001		
SKB62		No			VVF22.25-..		
					VVF22.40-..		
					VVF22.50-40		
					VVF22.65-63		
					VVF22.80-100		
					VXF22.25-..		
					VXF22.40-..		
					VXF22.50-40		
					VXF22.65-63		
					VXF22.80-100		
SKB62		No			VVF32.15-..		
					VVF32.25-..		
					VVF32.40-..		
					VVF32.50-40		
					VVF32.65-63		
					VVF32.80-100		
					VXF32.15-..		
					VXF32.25-..		
					VXF32.40-..		
					VXF32.50-40		


SKB62		No			VVF42.15-..		
					VVF42.20-6.3		
					VVF42.25-..		
					VVF42.32-16		
					VVF42.40-..		
					VVF42.50-40K		
					VVF42.50-..		
					VVF42.65-..		
					VVF42.65-63K		
					VVF42.80-..		
					VVF42.80-100K		
					VVF42.25-..C		
					VVF42.32-16C		
					VVF42.40-..C		
					VVF42.50-..C		
					VVF42.65-..C		
					VVF42.80-..C		
					VVF42.65KC		
					VVF42.80KC		
					VVF52.65-63KC		
					VVF52.80-100KC		
					VXF42.15-..		
					VXF42.20-6.3		
					VXF42.25-..		
					VXF42.32-16		
					VXF42.40-..		
					VXF42.50-..		
					VXF42.65-..		
					VXF42.80-..		
					VXF42.25-..C		
					VXF42.32-16C		
					VXF42.40-..C		
					VXF42.50-..C		
					VXF42.65-..C		
					VXF42.80-..C		
SKB62		No			VVF53.15-..		
					VVF53.20-6.3		
					VVF53.25-..		
					VVF53.32-16		
					VVF53.40-..		
					VVF53.50-31.5		
					VVF53.50-40		
					VVF53.50-40K		
					VXF53.15-..		
					VXF53.20-6.3		
					VXF53.25-..		
					VXF53.32-16		
					VXF53.40-..		
					VXF53.50-40		
SKB62		No			VVF61.09..11		
					VVF61.12..13		
					VVF61.14..15		
					VVF61.23..25		
					VVF61.39..40		
					VVF61.49..50		
					VXF61.14..15		
					VXF61.24..25		
					VXF61.39..40		
					VXF61.49..50		

SKB62		No			VVF63.15-0.2		
					VVF63.15-0.32		
					VVF63.15-0.5		
					VVF63.15-0.8		
					VVF63.15-1.25		
					VVF63.15-2		
					VVF63.15-3.2		
					VVF63.20-6.3		
					VVF63.25-5		
					VVF63.25-8		
					VVF63.32-16		
					VVF63.40-12.5		
					VVF63.40-20		
					VVF63.50-31.5		
					VVF63.50-40K		
					VVF63.65-50		
					VXF63.15-1.6		
					VXF63.15-2.5		
					VXF63.15-4		
					VXF63.20-6.3		
					VXF63.25-6.3		
					VXF63.25-10		
					VXF63.32-16		
					VXF63.40-16		
					VXF63.40-25		
					VXF63.50-31.5		







Actuator acting direction		 Direct acting Reverse acting Acting direction: Direct Acting direction: Reverse							
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
	ON OFF DC 4...20 mA DC 0...10 V 0% = 0 mm 100% = 100 mm						VVG41.11...12 VVG41.13 VVG41.14 VVG41.15 VVG41.20 VVG41.25 VVG41.32 VVG41.40 VVG41.50 VVG41.15 VVG41.20 VVG41.25 VVG41.32 VVG41.40 VVG41.50 VVG41.1301 VVG41.1401 VVG41.1501 VVG41.2001 VVG41.2501 VVG41.3201 VVG41.4001 VVG41.5001		
SKB62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF22.25-... VVF22.40-... VVF22.50-40 VVF22.65-63 VVF22.80-100 VVF22.25-... VVF22.40-... VVF22.50-40 VVF22.65-63 VVF22.80-100		
SKB62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF32.15-... VVF32.25-... VVF32.40-... VVF32.50-40 VVF32.65-63 VVF32.80-100 VVF32.15-... VVF32.25-... VVF32.40-... VVF32.50-40 VVF32.65-63 VVF32.80-100		
SKB62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF42.15-... VVF42.20-6.3 VVF42.25-... VVF42.32-16 VVF42.40-... VVF42.50-40K VVF42.50-... VVF42.65-... VVF42.65-63K VVF42.80-... VVF42.80-100K VVF42.25-...C VVF42.32-16C VVF42.40-...C VVF42.50-...C VVF42.65-...C VVF42.80-...C VVF42.65KC VVF42.80KC VVF42.15-... VVF42.20-6.3 VVF42.25-... VVF42.32-16 VVF42.40-... VVF42.50-... VVF42.65-... VVF42.65-63K VVF42.80-... VVF42.80-100K VVF42.25-...C VVF42.32-16C VVF42.40-...C VVF42.50-...C VVF42.65-...C VVF42.80-...C		
SKB62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF52.65-63KC VVF52.80-100KC		













SKB62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF53.15-...		
							VVF53.20-6.3		
							VVF53.25-...		
							VVF53.32-16		
							VVF53.40-...		
							VVF53.50-31.5		
							VVF53.50-40		
							VVF53.50-40K		
							VXF53.15-...		
							VXF53.20-6.3		
SKB62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VXF53.25-...		
							VXF53.32-16		
							VXF53.40-...		
							VXF53.50-40		
							VXF61.09..11		
							VXF61.12..13		
							VXF61.14..15		
							VXF61.23..25		
							VXF61.39..40		
							VXF61.49..50		
SKB62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VXF61.14..15		
							VXF61.24..25		
							VXF61.39..40		
							VXF61.49..50		
							VVF63.15-0.2		
							VVF63.15-0.32		
							VVF63.15-0.5		
							VVF63.15-0.8		
							VVF63.15-1.25		
							VVF63.15-2		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF63.15-3.2		
							VVF63.20-6.3		
							VVF63.25-5		
							VVF63.25-8		
							VVF63.32-16		
							VVF63.40-12.5		
							VVF63.40-20		
							VVF63.50-31.5		
							VVF63.50-40K		
							VVF63.65-50		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF63.15-1.6		
							VXF63.15-2.5		
							VXF63.15-4		
							VXF63.20-6.3		
							VXF63.25-6.3		
							VXF63.25-10		
							VXF63.32-16		
							VXF63.40-16		
							VXF63.40-25		
							VXF63.50-31.5		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVG41.11..12		
							VVG41.13		
							VVG41.14		
							VVG41.15		
							VVG41.20		
							VVG41.25		
							VVG41.32		
							VVG41.40		
							VVG41.50		
							VVG41.15		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVG41.20		
							VVG41.25		
							VVG41.32		
							VVG41.40		
							VVG41.50		
							VVG41.1301		
							VVG41.1401		
							VVG41.1501		
							VVG41.2001		
							VVG41.2501		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVG41.3201		
							VVG41.4001		
							VVG41.5001		









SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF22.25-...		
							VVF22.40-...		
							VVF22.50-40		
							VVF22.65-63		
							VVF22.80-100		
							VXF22.25-...		
							VXF22.40-...		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF32.15-...		
							VVF32.25-...		
							VVF32.40-...		
							VVF32.50-40		
							VVF32.65-63		
							VVF32.80-100		
							VXF32.15-...		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF42.15-...		
							VVF42.20-6.3		
							VVF42.25-...		
							VVF42.32-16		
							VVF42.40-...		
							VVF42.50-40K		
							VVF42.50-...		
							VVF42.65-...		
							VVF42.65-63K		
							VVF42.80-...		
							VVF42.80-100K		
							VVF42.25-...C		
							VVF42.32-16C		
							VVF42.40-...C		
							VVF42.50-...C		
							VVF42.65-...C		
							VVF42.80-...C		
							VVF42.65KC		
							VVF42.80KC		
							VXF42.15-...		
							VXF42.20-6.3		
							VXF42.25-...		
							VXF42.32-16		
							VXF42.40-...		
							VXF42.50-...		
							VXF42.65-...		
							VXF42.80-...		
							VXF42.25..C		
							VXF42.32-16C		
							VXF42.40..C		
							VXF42.50..C		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF52.65-63KC		
							VVF52.80-100KC		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF53.15-...		
							VVF53.20-6.3		
							VVF53.25-...		
							VVF53.32-16		
							VVF53.40-...		
							VVF53.50-31.5		
							VVF53.50-40		
							VVF53.50-40K		
							VXF53.15-...		
							VXF53.20-6.3		
							VXF53.25-...		
SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF53.32-16		
							VXF53.40-...		
							VXF53.50-40		
							VVF61.09..11		
							VVF61.12..13		
							VVF61.14..15		
							VVF61.23..25		
							VVF61.39..40		
							VVF61.49..50		
							VXF61.14..15		
							VXF61.24..25		
							VXF61.39..40		
							VXF61.49..50		





SKB62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF63.15-0.2		
							VVF63.15-0.32		
							VVF63.15-0.5		
							VVF63.15-0.8		
							VVF63.15-1.25		
							VVF63.15-2		
							VVF63.15-3.2		
							VVF63.20-6.3		
							VVF63.25-5		
							VVF63.25-8		
							VVF63.32-16		
							VVF63.40-12.5		
							VVF63.40-20		
							VVF63.50-31.5		
							VVF63.50-40K		
							VVF63.65-50		
							VXF63.15-1.6		
							VXF63.15-2.5		
							VXF63.15-4		
							VXF63.20-6.3		
							VXF63.25-6.3		
							VXF63.25-10		
							VXF63.32-16		
							VXF63.40-16		
							VXF63.40-25		
							VXF63.50-31.5		





Actuator acting direction		Direct acting Reverse acting Positioning signal Y: DC 0...10 V 4...20 mA Positioning signal Z: 0...1000 □ — Acting direction: Direct - - - Acting direction: Reverse					
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
	ON OFF DC 4...20 mA DC 0...10 V lin = linear log = gleichprozentig						
*This setting can lead to strong oscillation behavior. This setting should be avoided if possible.							
SKC62		Yes			VVF22.100-160		
SKC62		Yes			VXF22.100-160		
SKC62		Yes			VVF32.100-160		
					VVF32.125-250		
					VVF32.150-400		
SKC62		Yes			VXF32.100-160		
					VXF32.125-250		
					VXF32.150-400		
SKC62		Yes			VVF42.100-...		
					VVF42.100-160K		
					VVF42.100-...C		
					VVF42.100KC		
					VVF42.125-...		
					VVF42.150-...		
					VVF42.125-250K		
					VVF42.150-360K		
					VVF42.125-...C		
					VVF42.150-...C		
					VVF42.125KC		
					VVF42.150KC		


SKC62		Yes			VXF42.100-...		
					VXF42.100..C		
					VXF42.100KC		
					VXF42.125-...		
					VXF42.150-...		
					VXF42.125..C		
					VXF42.150..C		
SKC62		Yes			VVF43.65-50		
					VVF43.65-63		
					VVF43.80-80		
					VVF43.80-100		
					VVF43.100-125		
					VVF43.100-160		
					VVF43.125-200		
					VVF43.125-250		
					VVF43.150-315		
					VVF43.150-400		
					VVF43.65-63K		
					VVF43.80-100K		
					VVF43.100-150K		
					VVF43.125-220K		
					VVF43.150-315K		
					VVF43.200-450K		
					VVF43.250-630K		
SKC62		Yes			VXF43.65-50		
					VXF43.65-63		
					VXF43.80-80		
					VXF43.80-100		
					VXF43.100-125		
					VXF43.100-160		
					VXF43.125-200		
					VXF43.125-250		
					VXF43.150-315		
					VXF43.150-400		
SKC62		Yes			VVF52.100-160KC		
					VVF52.125-200KC		
					VVF52.150-315KC		








SKC62		Yes			VVF53.65-63		
					VVF53.80-100		
					VVF53.100-160		
					VVF53.125-250		
					VVF53.125-220K		
					VVF53.150-400		
					VVF53.150-315K		
					VVF53.65-63K		
					VVF53.80-100K		
					VVF53.100-150K		
					VVF53.200-450K		
					VVF53.250-630K		
					VXF53.65-63		
					VXF53.80-100		
					VXF53.100-160		
					VXF53.125-250		
					VXF53.150-400		
SKC62		Yes			VVF61.65		
					VVF61.80		
					VVF61.90		
					VVF61.91		
					VVF61.92		
					VXF61.65		
					VXF61.80		
					VXF61.90		
					VXF61.91		
					VXF61.92		
SKC62		Yes			VVF63.65-50		
					VVF63.80-80		
					VVF63.100-125		
					VVF63.125-200		
					VVF63.150-315		
SKC62		Yes			VVF63.65-63K		
					VVF63.80-100K		
					VVF63.100-150K		
					VVF63.125-220K		
					VVF63.150-315K		
SKC62		Yes			VXF63.65-50		
					VXF63.80-80		
					VXF63.100-125		
					VXF63.125-200		
					VXF63.150-315		

















SKC62		No			VVF22.100-160		
SKC62		No			VXF22.100-160		
SKC62		No			VVF32.100-160		
					VVF32.125-250 *		
					VVF32.150-400 *		
SKC62		No			VXF32.100-160		
					VXF32.125-250 *		
					VXF32.150-400 *		
SKC62		No			VVF42.100-..		
					VVF42.100-160K		
					VVF42.100-..C		
					VVF42.100KC		
					VVF42.125-.. *		
					VVF42.125-250K *		
					VVF42.150-.. *		
					VVF42.150-360K *		
					VVF42.125-..C		
					VVF42.150-..C		
					VVF42.125KC		
					VVF42.150KC		
SKC62		No			VXF42.100-..		
					VXF42.100..C		
					VXF42.125-.. *		
					VXF42.150-.. *		
					VXF42.125..C		
					VXF42.150..C		








SKC62		No			VVF43.65-50		
					VVF43.65-63		
					VVF43.65-63K		
					VVF43.80-80		
					VVF43.80-100		
					VVF43.80-100K		
					VVF43.100-125		
					VVF43.100-160		
					VVF43.100-150K		
					VVF43.125-200 *		
					VVF43.125-250 *		
					VVF43.125-220K *		
					VVF43.150-315 *		
					VVF43.150-400 *		
					VVF43.150-315K *		
					VVF43.200-450K		
					VVF43.250-630K		
SKC62		No			VXF43.65-50		
					VXF43.65-63		
					VXF43.80-80		
					VXF43.80-100		
					VXF43.100-125		
					VXF43.100-160		
					VXF43.125-200 *		
					VXF43.125-250 *		
					VXF43.150-315 *		
					VXF43.150-400 *		
SKC62		No			VVF52.100-160KC		
					VVF52.125-200KC		
					VVF52.150-315KC		
SKC62		No			VVF53.65-63		
					VVF53.65-63K		
					VVF53.80-100		
					VVF53.80-100K		
					VVF53.100-160		
					VVF53.100-150K		
					VVF53.125-250 *		
					VVF53.125-220K *		
					VVF53.150-400 *		
					VVF53.150-315K *		
					VVF53.200-450K		
					VVF53.250-630K		
					VXF53.65-63		
					VXF53.80-100		
					VXF53.100-160		
					VXF53.125-250 *		
					VXF53.150-400 *		















SKC62		No			VVF61.65		
					VVF61.80		
					VVF61.90		
					VVF61.91		
					VVF61.92		
					VXF61.65		
					VXF61.80		
					VXF61.90		
					VXF61.91		
					VXF61.92		
SKC62		No			VVF63.65-50		
					VVF63.80-80		
					VVF63.100-125		
					VVF63.125-200 *		
					VVF63.150-315 *		
SKC62		No			VVF63.65-63K		
					VVF63.80-100K		
					VVF63.100-150K		
					VVF63.125-220K *		
					VVF63.150-315K *		
SKC62		No			VXF63.65-50		
					VXF63.80-80		
					VXF63.100-125		
					VXF63.125-200 *		
					VXF63.150-315 *		

Actuator acting direction		 Direct acting Reverse acting Acting direction: Direct Acting direction: Reverse							
Actuator ASN	DIL Switch Config	Factory Setting	Actuator stroke / angle characteristic	Actuator U-Signal	Modbus Cableadapter Setting	Modbus Cableadapter Factory Setting	Valve ASN	Valve stroke / angle characteristic	Actuator + valve characteristic
ON OFF DC 4...20 mA DC 0...10 V 0h = linear Reg = piecewise linear									
*This setting can lead to strong oscillation behavior. This setting should be avoided if possible.									
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF22.100-160		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VXF22.100-160		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF32.100-160		
							VVF32.125-250		
							VVF32.150-400		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VXF32.100-160		
							VXF32.125-250		
							VXF32.150-400		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF42.100-...		
							VVF42.100-160K		
							VVF42.100-...C		
							VVF42.100KC		
							VVF42.125-...		
							VVF42.150-...		
							VVF42.125-250K		
							VVF42.150-360K		
							VVF42.125-...C		
							VVF42.150-...C		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF42.125KC		
							VVF42.150KC		
							VXF42.100-...		
							VXF42.100-...C		
							VXF42.125-...		
							VXF42.150-...		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VXF42.125-...C		
							VXF42.150-...C		
							VXF42.125-...C		
							VXF42.150-...C		

SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF43.65-50		
							VVF43.65-63		
							VVF43.80-80		
							VVF43.80-100		
							VVF43.100-125		
							VVF43.100-160		
							VVF43.125-200		
							VVF43.125-250		
							VVF43.150-315		
							VVF43.150-400		
							VVF43.65-63K		
							VVF43.80-100K		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VXF43.65-50		
							VXF43.65-63		
							VXF43.80-80		
							VXF43.80-100		
							VXF43.100-125		
							VXF43.100-160		
							VXF43.125-200		
							VXF43.125-250		
							VXF43.150-315		
							VXF43.150-400		
							VVF52.100-160KC		
							VVF52.125-200KC		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF52.150-315KC		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF53.65-63		
							VVF53.80-100		
							VVF53.100-160		
							VVF53.125-250		
							VVF53.125-220K		
							VVF53.150-400		
							VVF53.150-315K		
							VVF53.65-63K		
							VVF53.80-100K		
							VVF53.100-150K		
							VVF53.200-450K		
							VVF53.250-630K		
							VXF53.65-63		
							VXF53.80-100		
							VXF53.100-160		
							VXF53.125-250		
							VXF53.150-400		

SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF61.65		
							VVF61.80		
							VVF61.90		
							VVF61.91		
							VVF61.92		
							VXF61.65		
							VXF61.80		
							VXF61.90		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF63.65-50		
							VVF63.80-80		
							VVF63.100-125		
							VVF63.125-200		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF63.150-315		
							VVF63.65-63K		
							VVF63.80-100K		
							VVF63.100-150K		
							VVF63.125-220K		
SKC62/MO		Yes			LIN (Reg 263 = 0) (Reg 264 = 500)	Yes	VVF63.150-315K		
							VXF63.65-50		
							VXF63.80-80		
							VXF63.100-125		
							VXF63.125-200		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF22.100-160		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF22.100-160		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF32.100-160		
							VVF32.125-250 *		
							VVF32.150-400 *		

SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF32.100-160		
							VXF32.125-250 *		
							VXF32.150-400 *		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF42.100-...		
							VVF42.100-160K		
							VVF42.100-...C		
							VVF42.100KC		
							VVF42.125KC		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF42.150KC		
							VVF42.125-... *		
							VVF42.125-250K *		
							VVF42.150-... *		
							VVF42.150-360K *		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF42.100-...		
							VXF42.100...C		
							VXF42.100KC		
							VXF42.125-... *		
							VXF42.150-... *		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF42.125...C		
							VXF42.150...C		
							VVF43.65-50		
							VVF43.65-63		
							VVF43.65-63K		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF43.80-80		
							VVF43.80-100		
							VVF43.80-100K		
							VVF43.100-125		
							VVF43.100-160		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF43.100-150K		
							VVF43.125-200 *		
							VVF43.125-250 *		
							VVF43.125-220K *		
							VVF43.150-315 *		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF43.150-400 *		
							VVF43.150-315K *		
							VVF43.200-450K		
							VVF43.250-630K		
							VVF43.250-630K		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF43.65-50		
							VXF43.65-63		
							VXF43.80-80		
							VXF43.80-100		
							VXF43.100-125		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VXF43.100-160		
							VXF43.125-200 *		
							VXF43.125-250 *		
							VXF43.150-315 *		
							VXF43.150-400 *		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF52.100-160KC		
							VVF52.125-200KC		
							VVF52.150-315KC		

SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF53.65-63		
							VVF53.65-63K		
							VVF53.80-100		
							VVF53.80-100K		
							VVF53.100-160		
							VVF53.100-150K		
							VVF53.125-250 *		
							VVF53.125-220K *		
							VVF53.150-400 *		
							VVF53.150-315K *		
							VVF53.200-450K		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF53.250-630K		
							VXF53.65-63		
							VXF53.80-100		
							VXF53.100-160		
							VXF53.125-250 *		
							VXF53.150-400 *		
							VVF61.65		
							VVF61.80		
							VVF61.90		
							VVF61.91		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF61.92		
							VXF61.65		
							VXF61.80		
							VXF61.90		
							VXF61.91		
							VXF61.92		
							VVF63.65-50		
							VVF63.80-80		
							VVF63.100-125		
							VVF63.125-200 *		
SKC62/MO		No			LOG (Reg 263 = 1) Combination will not work. (Problem with valve jam detection)	No	VVF63.150-315 *		
							VVF63.65-63K		
							VVF63.80-100K		
							VVF63.100-150K		
							VVF63.125-220K *		
							VVF63.150-315K *		
							VXF63.65-50		
							VXF63.80-80		
							VXF63.100-125		
							VXF63.125-200 *		
							VXF63.150-315 *		